



CR 3

GRUNDFOS 

ردیف	مدل	ولتاژ و فاز	RPM	توان موتور P _r HP	توان موتور P _r KW	شدت جریان	حداکثر هد (متر)	حداقل هد (متر)	حداکثر دبی (متر مکعب در ساعت)	قطر دهانه ورودی mm	قطر دهانه خروجی mm
2	CR 3-9	3×380-415Y	2870	1	0/75	1/9	60	23	1.2 - 4.46	1"/1¼"	1"/1¼"
3	CR 3-11	3×380-415Y	2870	1/5	1/1	2/5	73/17	28/33	1.2 - 4.5	1"/1¼"	1"/1¼"
4	CR 3-12	3×380-415Y	2870	1/5	1/1	2/5	80	30	1.2 - 4.47	1"/1¼"	1"/1¼"
5	CR 3-13	3×380-415Y	2870	1/5	1/1	2/5	86/28	33/14	1.2- 4.46	1"/1¼"	1"/1¼"
6	CR 3-15	3×380-415Y	2870	1/5	1/1	2/5	99	37/18	1.2- 4.44	1"/1¼"	1"/1¼"
7	CR 3-17	3×380-415Y	2970	2	1/5	3/15	113/7	44/23	1.2-4.52	1"/1¼"	1"/1¼"
8	CR 3-19	3×380-415Y	2910	2	1/5	3/15	126/7	44/33	1.2-4.51	1"/1¼"	1"/1¼"
9	CR 3-21	3×380-415Y	2910	3	2/2	4/45	140	55/95	1.2-4.54	1"/1¼"	1"/1¼"
10	CR 3-23	3×380-415Y	2910	3	2.2	4/45	154	60	1.2-4.53	1"/1¼"	1"/1¼"
11	CR 3-25	3×380-415Y	2910	3	2/2	4/45	167/1	67/08	1.2-4.51	1"/1¼"	1"/1¼"

۰۲۱-۳۶۶۱۳۴۴۰

۰۲۱-۳۳۹۰۵۴۳۵